

## HANDHELD SIGNAL JAMMER P27-6B-EU



### Instructions

- ✓ Built-in battery, 2-3 hours working, charged by home charger or car cigarette lighter
- ✓ Support long working hour (can be used in charging);
- ✓ Obvious power indicator with separate switch control;
- ✓ Gas, petrol station, oil depot

### Features

- The efficient RF chip applied
- Adopting slow art circuit design to avoid ignition
- Using metal aluminum shell
- Transmitting power is 3w, shielding distance is 1-5m
- Harmless to human body

### Specification :

Item	Bands	Frequency	Average output power	Transmitting output power (W)
1	Band 20	791~821MHz	27dBm	0.5W
2	Band 8	925~960 MHz	27dBm	0.5W
3	GPS	1550~1580 MHz	27dBm	0.5W
4	Band 3	1805~1880 MHz	27dBm	0.5W
5	Band 1	2110~2170 MHz	27dBm	0.5W
6	Band 7	2620~2690 MHz	27dBm	0.5W

Size: 130(L)×75(W)×35(H)

Weight: 800g

Power supply: input AC 110-240 output DC:4.2V