

## GFQ-D-0727 Cavity Power Splitter Series

- Suitable for 700 to 2700MHz band, Divide high power signal averagely
- Low VSWR, Low insertion loss
- Widely applied to single band, multiband antenna or leakage cable system

Specifications			
Category	2 way splitter	3 way splitter	4 way splitter
Model	GFQ-2D-0727	GFQ-3D-0727	GFQ-4D-0727
Frequency Range -MHz	700 to 2700		
Insertion Loss(Including Dividing Loss)-dB	≤3.2	≤5.2	≤6.3
Nominal Impedance -Ω	50		
VSWR	≤1.3		
Maximum Power-W	Average 500 (Peak Value 3000)		
Connector	N Female		
Temperature -°C	-35 to +75		
Dimensions -mm	215×67×29	270×67×29	270×67×48
Weight -g	280	360	390



### Kenbotong Technology Co., Ltd.

Addr : NO.2 Chanxiu Road ,Foshan city,Guangdong China

Code: 528061

Tel: 86(757)8202-5597, 8221-9788

Fax : 86(757)8221-2072,8802-2808

Email: kbt@kenbotong.com

web: <http://www.kenbotong.com>