

5G SIGNAL JAMMER P35-12B-EU



Application

- ✓ Education Industry, examination room, social examination centers
- ✓ Troops, confidential places, concert halls
- ✓ Prison, detention center, court
- ✓ Gas, petrol station, oil depot

Features

- The efficient RF chip applied
- Adopting slow art circuit design to avoid ignition,
- Using metal aluminum shell
- Transmitting power is 30w, shielding distance is 3-15 m
- Harmless to human body
- Circuit output controlled separately

Specification :

Item	Bands	Frequency	Average output power	Transmitting output power (W)
1	Band 20	791 ~ 821 MHz	35dBm	3W
2	Band 8	925 ~ 960 MHz	35dBm	3W
3	GPS	1550 ~ 1580 MHz	35dBm	3W
4	Band 3	1805 ~ 1880 MHz	33dBm	2W
5	Band 1	2110 ~ 2200 MHz	33dBm	2W
6	Band 40&2.4G WiFi	2300 ~ 2500 MHz	33dBm	2W
7	Band 7& 2.4G WiFi	2500 ~ 2700 MHz	33dBm	2W
8	N78A	3330 ~ 3530 MHz	33dBm	2W
9	N78B	3570 ~ 3770 MHz	33dBm	2W
10	5.2G WiFi	5200 ~ 5400 MHz	33dBm	2W
11	VHF	136 ~ 174 MHz	35dBm	3W
12	UHF	400 ~ 470 MHz	35dBm	3W

Size: 295(L)×240(W)×55(H)

Weight : 4.2KG

Power supply: input AC 110-240 output DC:12V 13A